

APPENDIX A

Atari-Specific Manual Pages

Following is a list of changes, additions, and omissions that characterize the difference between the Atari System V on-line manual pages and the AT&T 3B2 manual page documentation. Some differences have to do with the nature of the Atari port, others are Atari enhancements.

Manual pages for commands and files that have been changed or added are available on-line by using the **man(1)** command. For example, for information about gcc, type **man gcc**.

Use the permuted index in the *AT&T Product Overview and Master Index* to locate specific manual pages in the manuals

Changes

These manual pages were changed to accommodate the Atari System V port.

cunix(1M)	edt_data(4)
format(1M)	master(4)
prvtoc(1M)	
newboot(1M)	

Additions

The following manual pages contain Atari System V enhancements.

bison(1)	patch(1)
ci(1)	psc(1)
co(1)	rcs(1)
codesio(1)	rcsdiff(1)
findsrc(1)	rcsintro(1)
gcc(1)	rcsmerge(1)
g++(1)	rlog(1)
gdb(1)	sc(1)
glscnv(1)	shar(1)
glstty(1)	unshar(1)
gnudiff(1)	
hex(1)	bootaddhdr(1M)
ident(1)	bpatch(1M)
indent(1)	consmode(1M)
kermi(1)	e(1M)
less(1)	nvr(1M)imagpartini
lesskey(1)	t(1M)
makekit(1)	setlang(1M)
merge(1)	setnetwork(1M)
mush(1)	setvtoc(1M)

sysm68k(2)	position(3A)
addchildhandler(3A)	readfiledata(3A)
addioproc(3A)	readfilelines(3A)
addpath(3A)	readfilestrings(3A)
alertinit(3A)	readpipedata(3A)
atarilib(3A)	readpipelines(3A)
closepipe(3A)	readpipestrings(3A)
executelist(3A)	runprocess(3A)
findwmpadding(3A)	writefiledata(3A)
fmcatsgets(3)	writefilelines(3A)
fmcatsopen(3A)	writepipedata(3A)
getcommandstatus(3A)	writepipelines(3A)
getpipeid(3A)	getedt(3C)
getsimplecharset(3A)	getxedt(3C)
helpinit(3A)	
logopen(3A)	rcsfile(5)
logwrite(3A)	
openfilter(3A)	gls(7)
openreadpipe(3A)	
openwritepipe(3A)	boot(8)
	edtp(8)

Omissions

Not a part of Atari System V.

crash	ledre
disks	login
editsa	pump
edittbl	sadp
cmpress	wtinit
fltboot	xts
fmtflop	xtt
fmthard	zdump
ismpx	XWIN X11/NeWS server
jterm	X11/NeWS, tNt and Shapes
jwin	API toolkits
layers	EMD
ldsysdump	3B2 Floppy Disk Driver ...
	AT&T Windowing Utilities

APPENDIX B

Boot Text

BOOT TEXT OUTPUT TO THE CONSOLE

The screen starts blank. After a 90-second time out (or when any key is depressed), the following message appears:

Atari System V.4 Fri Jun 7 14:02:04 EDT 1991

This message appears only on the console, not on a terminal output of the USART port. The date and message may change, depending on the specific generation of the System V boot.

The next section of information appears on both console and the USART port.

This information differs, depending on the specific configurations of SCSI devices connected to the machine. Every SCSI device should appear on this list.

Now there is a time-out of about 20 seconds. As administrator you may press <Return> to skip the pause.

The no devices found message means that those specific devices are not physically connected to the system.

SCSI:

TARGET LUN

0 0 MAXTOR LXT-213S 4.20 Direct access

UNIX System V Release 4.0 Boot Loader

Boot: hd(0,0)unix

Building Equipped Device Table

CEN: controller 0 at 0xFFFFF8800

CLOCK: controller 0 at 0xFFFFF8960

FPD: controller 0 at 0xFFFFF8606

HD: controller 0 at 0x0

IKBD: controller 0 at 0xFFFFFC00

LA: no devices found

MFP: controller 0 at 0xFFFFFA01

ND: no devices found

PR: no devices found

PSG: controller 0 at 0xFFFFF8800

SCCIO: controller 0 at 0xFFFFF8C80

SCSI: controller 0 at 0xFFFFF8780

TP: no devices found

VIDEO: controller 0 at 0x0

USART: controller 0 at 0xFFFFFA01

Loading unix: 820 + 0[193192] + 722896 + 93432 + 864

**UniSoft UNIX (R) System V Release 4.0
Version UE10 for the mc68030**

Total real memory = 8388608

Available memory = 6664192

These numbers vary, depending on the amount of memory installed on the system and the configuration of the kernel.

The screen clears and is replaced by the gray background of root X Window; then the login screen is displayed.

This line varies, depending on the node name of the system.

Memory and device configuration will vary.

Copyright (c) 1984, 1986, 1987, 1988, 1989 AT&T-All Rights Reserved

THIS IS UNPUBLISHED PROPRIETARY SOURCE CODE OF AT&T INC.
The copyright notice above does not evidence any actual or intended publication of such source code.
Portions provided by UniSoft Corp. under a development agreement with AT&T and Motorola.

*Node: noname

MOTOROLA M68K SYSTEM CONFIGURATION

Memory size: 8 Megabytes

System Peripherals:

Device Name

CEN
CLOCK
FFD
HD

MAXTOR LXT-213S 4.20 0 203 Mbytes

IKBD
MFP
PSG
SCCIO
SCSI
USART
VIDEO

SYSTEM V STREAMS TCP Release 1.0

(c) 1983,1984,1985,1986,1987,1988,1989 AT&T.
(c) 1986,1987,1988,1989 Sun Microsystems.
(c) 1987,1988,1989 Lachman Associates, Inc. (LAI).
All Rights Reserved.

The system is ready.

APPENDIX C

References

Atari Computer Corporation, *ATARI TT Computer Owners Manual*, Atari Corporation, 1990

Atari Computer Corporation, *Atari Style*, Atari Corporation, 1991

AT&T, *UNIX System V Release 4*, Prentice-Hall, Inc., 1990—the following:

Device Driver Interface/Driver Kernel Interface
Network User's and Administrator's Guide
Product Overview and Masters Index
Programmer's Guide: BSD/XENIX Compatibility Guide
Programmer's Guide: Networking Interfaces
Programmer's Guide: STREAMS
Programmer's Guide: System Services and Application Packaging Tools
Programmer's Reference Manual
System Administrator's Guide
System Administrator's Reference Manual
System Services and Application Packaging Tools
User's Guide
User's Reference Manual

Bach, M.J., *The Design of the UNIX Operating System*, Prentice-Hall, 1986

Bourne, S., *The Unix System V Environment*,

McGilton, and Morgan, *Introducing Unix System V*, McGraw Hill, 1983

Non Standard Logics, *WISh2 User's Manual*, Paris, France, 1991

Non Standard Logics, *WX2 User's Guide*, Paris, France, 1991

Non Standard Logics, *XFaceMaker 2 User's Guide for Use With Version 1.0*

Nye, A. and O'Reilly, T., published by O'Reilly & Associates, 1990—the following:

Volume One, Xlib Programming Manual for Version 11
Volume Two, Xlib Reference Manual for Version 11
Volume Four, : X Toolkit Intrinsics Programming Manual
Volume Five, X Toolkit Intrinsics Reference Manual for X Version 11

Open Software Foundation, Prentice Hall Inc., 1990—the following:

OSF/Motif Programmer's Guide, Revision 1.0
OSF/Motif Programmer's Reference, Revision 1.1
OSF/Motif Style Guide, Revision 1.1
OSF/Motif User's Guide, Revision 1.0

Sobell, M., *A Practical Guide to Unix System V*—Second Edition, Release 4, Benjamin Cumming Publishing Company, 1991

Young, D. A., *The X Window System—Programming and Applications with Xt: OSF/Motif Edition*, Prentice-Hall, Inc., 1990

X/Open Company, Ltd, *X/Open Portability Guide, XSI Supplementary Definitions*, Prentice-Hall, Inc.

APPENDIX D

GEM/Xlib Equivalents

The following table of GEM/Xlib equivalents will help you find the Xlib function equivalent to a GEM function. The parameter **display** is always the returned display pointer from XOpenDisplay.

X provides several routines for drawing. The graphic context (GC) resource specifies variables such as color, line width, and fill pattern. A GC is specified as an argument to the drawing routine and modifies its appearance. For more details about the GC and how to write programs using Xlib, see the *Xlib Programming Manual*.

The table contains the most frequently used GEM functions, their Xlib equivalents, and the page number for the function description in the *Xlib Reference Manual*. Instead of attribute functions for each graphic primitive such as GEM has, Xlib uses only one function to set an attribute for all graphic primitives. In general, setting a GC attribute affects the drawing of every graphic primitive call.

VDI—Xlib Equivalents

Frequently Used GEM Functions	Xlib Equivalents	Page No.
v_arc(handle, x, y, radius, begin_angle, end_angle)	XDrawArc(display, drawable, gc, x, y, w, h, angle1, angle2) XFillArc(display, drawable, gc, x, y, w, h, angle1, angle2) XSetArcMode(display, gc, arc_mode)	134 172 397
v_bar(handle, xarray)	XFillRectangle(display, drawable, gc, x, y, w, h)	178
v_circle(handle, x, y, radius)	XDrawArc(display, drawable, gc, x, y, w, h, angle1, angle2) XFillArc(display, drawable, gc, x, y, w, h, angle1, angle2) XSetArcMode(display, gc, arc_mode)	134 172 397
v_cisvbk	XCloseDisplay(display)	81
v_ellarc	XDrawArc(display, drawable, gc, x, y, w, h, angle1, angle2) XFillArc(display, drawable, gc, x, y, w, h, angle1, angle2) XSetArcMode(display, gc, arc_mode)	134 172 397
v_ellipse	XDrawArc(display, drawable, gc, x, y, w, h, angle1, angle2) XFillArc(display, drawable, gc, x, y, w, h, angle1, angle2) XSetArcMode(display, gc, arc_mode)	134 172 397
v_enter_cur	no real equivalent for this under X; for terminal emulation open an xterm window	
v_exit_cur	no real equivalent for this under X; for terminal emulation open an xterm window	
v_get_pixel	XGetPixel(ximage, x, y) gets a pixel from an IMAGE, not the whole screen area	223

**VDI—Xlib
Equivalents,
continued**

Frequently Used GEM Functions	Xlib Equivalents	Page No.
v_gtext(handle, x, y, string)	XDrawString(display, drawable, gc, x, y, string, length_of_string)	157
	XDrawString16(display, drawable, gc, x, y, string, length_of_string)	159
	XDrawImageString(display, drawable, gc, x, y, string, length_of_string)	141
	XDrawImageString16(display, drawable, gc, x, y, string, length_of_string)	143

The most important functions that specify a drawing in a GC are

XSetArcMode()	XSetTile()
XSetClipMask()	XSetTSOrigin()
XSetClipOrigin()	XSetForeground()
XSetClipRectangles()	XSetGraphicExposures()
XSetRegion()	XSetSubwindowMode()
XSetDashes()	XSetBackground()
XSetLineAttributes()	XSetFunction()
XSetFillRule()	XSetPlaneMask()
XSetFillStyle()	XSetState()

Graphic primitives (drawing functions) are

XDraw()	XDrawRectangles()
XDrawArc()	XDrawSegments()
XDrawArcs()	XFillArc()
XDrawFilled()	XFillArcs()
XDrawLine()	XFillPolygon()
XDrawLines()	XFillRectangle()
XDrawPoint()	XFillRectangles()
XDrawPoints()	XClearArea()
XDrawRectangle()	XClearWindow()

See the *Xlib Reference Manual* for details about the functions.

APPENDIX E

Atari Enhancements to Internationalization Standards

Atari System V fully supports the X/Open Portability Guide, Issue 3 (xpg3) Standard for internationalization of programming and character sets. Included here is a table of Atari System V functions and the corresponding xpg3 function. Most functions are part of the standard C library, the others are Atari enhancements.

ATARI SYSTEM V	xpg3 FUNCTION	DESCRIPTION
catgets(3C)	catgets	Read message catalog
catopen(3C)	catopen, catclose	Open/close message catalog
ecvt(3C)	gcvt	Convert floating point number to string
ctime(3C)		Convert date and time to string
ctype(3C)	isalnum isalpha iscntrl isgraph islower isprint ispunct isspace isupper	Character handling
conv(3C)	tolower, toupper	Character translation
codesio(1) ²		Character code set compiler
getdate(3C)		Convert date and time format
gl(7) ²		Character mapping STREAMS module
glscnv(1) ²		Code set mapping test program
glsty(1) ²		Enables character mapping module
localeconv(3C) ¹		Get numeric formatting formats
mbchar(3C) ¹		Multibyte character handling
mbstring(3C) ¹		Multibyte string handling
nl_langinfo(3C)	nl_langinfo	Get local formats
perror(3C)	perror	Print system error messages
printf(3C)	printf fprintf sprintf	Print formatted output
regexp(5)	regexp	Regular expression matching
setlocale(3C)	setlocale	Get environment variables
scanf(3C)	scanf fscanf sscanf	Scan formatted input
¹ Conforms to ANSI x3.159 programming language C standard ² Atari enhancement		

ATARI SYSTEM V	xpg3 FUNCTION	DESCRIPTION
strcoll(3C)	strcoll	String collation
strerror(3C)	strerror	Get error message string
strtime(3C)	strtime	Convert date and time to string
string(3C)		String operations
strtod(3C)	strtod atof	Convert string to number
strxfrm(3C)	strxfrm	string transformations
vprintf(3C)	vprintf vfprintf vsprintf	Print formatted output

The standard headers are used to provide definitions and declarations for use with nationalized language functions:

ctype.h	See ctype(3C) manual page
langinfo.h	Language constants; see langinfo(5) manual page
limits.h	Operating system limits; see limits(4) manual page
locale.h	Catagory names; see setlocale(3C) manual page
nl_types.h	Language data types; see nl_types(5) manual page

Index

A

- Account ID, 3-1
- Accounts
 - Adding, 3-3
 - Disabling, 3-4
 - Guest, 3-3
 - Setting passwords, 3-5
 - Superuser, 3-2
- Accounts and groups, 3-1—3-6
- Adding a device driver, 4-12
- Adding a new terminal type, 3-26—3-27
- Adding a user account, 3-3
- Adding new disk drives, 3-27—3-33
- Administrative processes, 3-11
- Alert dialogs, 4-7
- Application development, 4-1—4-2
 - Libraries, 4-1—4-2
- Application errors. *See* Alert dialogs
- Application implementation, 4-6—4-10
- Application packaging, 4-10—4-11
- Atari boot preference, 3-41
- Atari library, 4-6
 - Alert dialogs, 4-7
 - Help processes, 4-7
 - Input/output routines, 4-8
 - Internationalization, 4-7
 - Log files, 4-9
 - Routines, 4-9—4-10
 - Running subprocesses, 4-8
 - Window construction, 4-6
- Atari partition table, 3-28—3-33
- Atari tools
 - Boot preference, 3-39—3-41
 - Console configuration, 2-4—2-6
 - File System, 3-18

- filesystems, 3-18
- Kernel Configuration, 3-33
- Product Install, 3-13

Audio bell, 2-5

B

- Backup commands, 3-7—3-10
 - tar, 3-9
- Bell settings, 2-5
- boot Command, 3-38
- Boot preference change, 3-39
- Booting the system, 1-2
- Bourne shell, 3-16

C

- C shell, 3-16
- Changing password, 2-3
- Checking file systems, 3-20
- codesio Command, 3-27
- Command, cpio, 3-8
- Command shells, 3-15
- Commands, 3-24
 - boot, 3-38
 - codesio, 3-27
 - cunix, 3-38
 - date, 3-11
 - dd, 3-7
 - find, 3-4
 - format, 3-28, 3-31
 - glscnv, 3-27
 - kill, 3-11
 - ld, 3-38
 - mkfs, 3-32
 - mount, 3-17, 3-20, 3-32
 - partinit, 3-28
 - passwd, 1-3
 - pmand, 3-23
 - ps, 3-11
 - rsh, 3-10
 - sacadm, 3-23
 - SETBOOT.PRGM, 3-39—3-40
 - setenv, 1-3
 - setvtoc, 3-31
 - share, 3-32

- shutdown, 3-13
- sysm68k, 3-39
- tar, 3-9
- unix, 1-3
- userdel, 3-5
- usermod, 3-4
- xdm, 3-15

- Communication services, 3-25
- Configure Unix, 3-33
- Console settings, 2-4
 - Bell adjustments, 2-5
 - Key click, 2-6
 - Keyboard adjustments, 2-5
 - Mouse adjustments, 2-5
 - Screen saver, 2-5
- cpio Command, 3-8
- cunix Command, 3-38

D

- Daemon processes, 3-11
- Data communication services, 3-25
- date Command, 3-11
- Date setting, 3-11
- dd Command, 3-7
- Default language, 1-3
- Default run level, 3-13
- Device drivers, 4-11—4-13
- Disabling user accounts, 3-4
- Disk drives, adding, 3-27—3-33
- Disk partitions, 3-30

E

- Equipped Device Table, 1-2
- Error messages, 4-7

F

- File system types, 3-18
- File systems, 3-16—3-21
 - Checking, 3-20
 - Disk space, 3-20
 - Mounting, 3-20
 - Unmounting, 3-20

find Command, 3-4, 3-8
format Command, 3-28, 3-31

G

glscnv Command, 3-27
Group ID, 3-1
Guest account, 3-3

H

Hardware installation, 1-2
Hardware requirements, 1-1
Help, 2-2
Help dialogs, 4-7

I

Input/output handling, 4-8
Install
 New application, 3-13
 New icon, 3-14
 Software updates, 1-4
Internationalization, 3-13, 3-26,
 4-3, 4-7

K

Kernel configuration, 3-33—3-37
 Build kernel, 3-37
 Change modules, 3-34
 Change parameters, 3-36
 Install kernel, 3-37
 Select kernel, 3-34
Key click settings, 2-6
Keyboard adjustments, 2-5
kill Command, 3-11
Korn shell, 3-16

L

Language additions, 4-4—4-6
Language applications, 2-3
Language changes, 3-13

Language locales, 4-5
Language settings, 1-3
ld Command, 3-38
Libraries, 4-1—4-2
 AtariLib, 4-2
 OSF/Motif, 4-2
 XFaceMaker 2, 4-2
 Xlib, 4-1
 Xtoolkit, 4-1
Library routines, 4-6
Log files, 4-9
Logging in to the system, 2-1
Login accounts, 1-4
Login screen, 1-4
lpadmin Command, 3-24

M

Maintaining file systems,
 3-19—3-21
Menu bar settings, 2-6
mkfs Command, 3-32
Modem connection, 3-24
Monitoring disk space, 3-20
mount Command, 3-17, 3-20,
 3-32
Mountable file systems, 3-17
Mounting file systems, 3-20
Mouse buttons, 2-1
Mouse settings, 2-5
Multiuser mode, 1-3
MWM, 2-1

N

Network access, 1-4
NFS options, 3-19
Nonvolatile memory, 3-39
NVRAM, 3-39

O

OSF/Motif window manager, 2-1

P

partinit Command, 3-28
Partition table, 3-28—3-33
passwd Command, 3-5
Password changes, 2-3
Peripheral devices, 3-21—3-26
pmand Command, 3-23
Port monitor, 3-22
Port monitor configuration, 3-23
Porting TOS/GEM applications,
 4-13—4-15
Preference files, 3-15
Printer connection, 3-24
Product install window, 3-13
Programming notes, 4-2
ps Command, 3-11
Public internet connection, 1-4

R

Reconfiguration, 3-37—3-39
Reconfigure Atari, 3-33
root account, 3-2
Root password, 1-3
rsh Command, 3-10
Run level change, 3-12
Run levels, 3-11
Running processes, 4-8

S

SAC command, 3-22
sacadm Command, 3-23
SAF command, 3-22
Screen Saver, 2-5
SCSI, definition, 1-2
Security, 3-6
Serial port configuration, 3-21
Serial port management, 3-21
Serial port modem, 3-24
Serial port printer, 3-24
Service access controller, 3-22
Service access facility,
 3-21—3-22

Set

- Bell, 2-5
- Date and time, 3-11
- Default language, 1-3
- Key click, 2-6
- Keyboard, 2-5
- Menu bar, 2-6
- Mouse, 2-5
- Root password, 1-3
- Screen saver, 2-5
- Time of day, 1-3
- X configuration window, 2-4

SETBOOT.PRg Command,
3-39—3-40

Setting account passwords, 3-5

setvtoc Command, 3-31

share Command, 3-32

shutdown command, 3-13

Software updates, 1-4

Superuser account, 3-2

sysm68k Command, 3-39

System

- Accounts, 3-1
- Administrative tasks, 3-1
- Backups, 3-6—3-10
- Environment, 3-10—3-16
- Groups, 3-1

Reconfiguration, 3-33—3-39

Security, 3-6

System installation, 1-2

System maintenance mode, 1-3

System processes, 3-11

Ethernet, 3-22

Port monitor, 3-22

Run level, 3-12

System reconfiguration, 3-33

T

tar Command, 3-9

Terminal types, adding,
3-26—3-27

Time of day, 1-3

Time setting, 3-11

Tools, 4-2

TOS boot preference, 3-40

ttymon process, 3-22

U

UFS options, 3-19

Unmounting file systems, 3-20

Unpacking Atari System V, 1-1

Upgrading a TT, 1-2

User accounts, 3-3

usermod Command, 3-4

UUCP support, 3-24

V

Variables, 3-10

Visual bell, 2-5

VTOC, creating, 3-31

W

Window construction, 4-6

WISH 2 windowing shell, 2-1

X

X configuration window, 2-4

X fonts, 3-27

X Window System, 3-15

xdm Command, 3-15

XFM applications, 4-6

